

The Catlink flush mount receiver head insert accommodates flush wall applications. Designed to click into PDL compatible wall plates this receiver head offers excellent reception angle and operation in bright or sunlit room situations.

Equipped with two screw terminals for connection to a receiver pair of a Catlink network and fully protected against accidental reverse connection or connection to telephone system voltages.

This version of the receiver head is passes fully modulated IR signals to the hub to maximise compatibility with difficult to repeat IR signalling and also has enhanced noise rejection capability for improved operation within close proximity of large plasma and LED panels.



PART# CL-IRM0338I

CATLINK receiver head insert



CATLINK receiver head insert mounted in wall plate.
PART# CL-IRM0338IP - special order only

Equipped with a blue 'Talk-back' indicator light mounted behind the Lens and flashes whenever infrared signals

Specifications

<i>Part Number</i>	<i>CL-IRM0338I</i>
<i>Typical Reception Range</i>	>4 meters in ambient light conditions. Reduces in bright sunlight conditions. Rated "Sunlight Friendly"
<i>Angle of operation</i>	Typ. over +/-60° from direct in front
<i>BP Centre Frequency</i>	38kHz
<i>IR Modulation Bandwidth</i>	30 ~ 60kHz
<i>Overall Length</i>	62mm